May 2009



# 1N4001 - 1N4007 General Purpose Rectifiers

### Features

- · Low forward voltage drop.
- High surge current capability.



**DO-41** COLOR BAND DENOTES CATHODE

Symbol	Parameter	Value						Units	
		4001	4002	4003	4004	4005	4006	4007	Units
V <sub>RRM</sub>	Peak Repetitive Reverse Voltage	50 100 200 400 600 800 1000		1000	V				
I <sub>F(AV)</sub>	Average Rectified Forward Current .375 " lead length @ T <sub>A</sub> = 75°C				1.0				А
I <sub>FSM</sub>	Non-Repetitive Peak Forward Surge Current 8.3ms Single Half-Sine-Wave	30		A					
l <sup>2</sup> t	Rating for Fusing (t<8.3ms)	3.7		A <sup>2</sup> sec					
T <sub>STG</sub>	Storage Temperature Range	-55 to +175		°C					
Т <sub>Ј</sub>	Operating Junction Temperature	-55 to +175			°C				

### Absolute Maximum Ratings \* T<sub>A</sub> = 25 °C unless otherwise noted

\* These ratings are limiting values above which the serviceability of any semiconductor device may by impaired.

### **Thermal Characteristics**

Symbol	Parameter	Value	Units	
PD	Power Dissipation	3.0	W	
$R_{ extsf{ heta}JA}$	Thermal Resistance, Junction to Ambient	50	°C/W	

### **Electrical Characteristics** $T_A = 25 \ ^{\circ}C$ unless otherwise noted

Symbol	Parameter	Value	Units
V <sub>F</sub>	Forward Voltage @ 1.0A	1.1	V
l <sub>rr</sub>	Maximum Full Load Reverse Current, Full Cycle $T_A = 75^{\circ}C$	30	μΑ
Ι <sub>R</sub>	$\begin{array}{llllllllllllllllllllllllllllllllllll$	5.0 50	μΑ μΑ
CT	Total Capacitance V <sub>R</sub> = 4.0V, f = 1.0MHz	15	pF

© 2009 Fairchild Semiconductor Corporation 1N4001 - 1N4007 Rev. C2 www.fairchildsemi.com

## Typical Performance Characteristics

Figure 1. Forward Current Derating Curve





Figure 3. Non-Repetitive Surge Current



**Figure 2. Forward Characteristics** 





Figure 4. Reverse Characteristics



### FAIRCHILD

#### SEMICONDUCTOR

#### TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

Auto-SPM™ Build it Now™ CorePLUS™ CORPOWER™ CROSSVOLT™ CTL™ Current Transfer Logic™ EcoSPARK<sup>®</sup> EfficentMax™ EZSWITCH™\*

Fairchild<sup>®</sup> Fairchild Semiconductor<sup>®</sup> FACT Quiet Series<sup>™</sup> FACT<sup>®</sup> FAST<sup>®</sup> FastvCore<sup>™</sup> FETBench<sup>™</sup> FlashWriter<sup>®</sup>\* FPS™ Global Power Resource SM Green FPS™ Green FPS™ e-Series™ Gmax™ GTO™ IntelliMAX™ ISOPLANAR™ MegaBuck™ MICROCOUPLER™ MicroFET™ MicroPak™ MillerDrive™ MotionMax™ Motion-SPM™ **OPTOLOGIC<sup>®</sup> OPTOPLANAR®** PDP SPM™ Power-SPM™

**F-PFS™** 

FRFFT<sup>®</sup>

PowerTrench<sup>®</sup> PowerXS<sup>™</sup> Programmable Active Droop™ QFET QS™ Quiet Series™ RapidConfigure™ Saving our world, 1mW/W/kW at a time™ SmartMax™ SMART START SPM® STEALTH™ SuperFET™ SuperSOT™-3 SuperSOT™-6 SuperSOT™-8 SupreMOS™ SyncFET™ Sync-Lock™ SYSTEM ®∗

The Power Franchise the power " franchise TinyBoost<sup>TM</sup> TinyBuckTM TinyDuckTM TinyOWOTOTM TinyPOwerTM TinyPWMTM TinyPWMTM TriFault DetectTM TRUECURRENTTM\*



UHC<sup>®</sup> Ultra FRFET™ UniFET™ VCX™ VisualMax™ XS™

\* Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

#### As used herein:

 Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.  A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

#### ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

#### **PRODUCT STATUS DEFINITIONS**

Definition of Terms		
Datasheet Identification	Product Status	Definition
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.